

RT-780 PGRALPHA Programming Procedure



To enter programming mode, follow the procedures below:

1. Press the **"Function Key"** twice to display the function menu. Press the **"Shift Right Key"** to move the cursor to **"ON/OFF PAGER"** – Press the **"Function Key"** to turn the pager OFF.
2. Press and hold **"Shift Left Key"** and **"Function Key"** keys for 2 seconds simultaneously. The screen will display **"1234"**. Default password is **"0000"**. With the cursor under the first digit **"1234"** press the **"Function Key"** to change the digit to **"0"**. Move cursor with **"Shift Right Key"** to the second digit **"0234"** and press the **"Function Key"** to change the value to **"0"**. Repeat for the 3rd and 4th digits.
3. On completion of above press the **"Read Key"** to access the main menu as below:

"ABFLPq"

A: Pager Capcode Setting

B: BPS

F: Frequency

L: Language

P: Password

q: Quit

- Use the **"Shift Key"** to scroll to the option you would like then use the **"Read Key"** to select:
- Option A will display as below:
 - **"A : 1234567 1 P"**
 - A: Number of Capcode – 1 to 6
 - 1234567: The seven digits of the pager capcode
 - 1: **1 = ON**, 0 = OFF
 - P: **P = Personal**, M = Mail Drop
 - Use the **"Shift Key"** to go under each number and **"Function Key"** to change numbers, after setting the capcodes, press the **"Read Key"** to return to the main program menu screen.
- Use the **"Shift Key"** to scroll between functions and the **"Function Key"** to select.
- Use the **"Function Key"** to scroll to group if you need to adjust
- After setting, select **q** and press the **"Read Key"** button to save the programmed information and return the pager to stand-by mode.